

Quick reference guide


Serena® Programming



Assign a Pico® wireless control to the shade

Step 1: Tap the **shade button** on all shades you want assigned to the control. The shade button illuminates green.

Step 2: Hold the **Close** button on the Pico for about 10 seconds, until the shade button blinks and turns off.



Honeycomb shade

Adjust the shade's lower and upper limits

Note: Shade must be assigned to control. See reverse side for diagram.


Lower Limit:

Step 1: Tap the **shade button** on the shade you want to adjust. The shade button illuminates green.

Step 2: Hold the **Open** and **Raise** buttons simultaneously on the Pico for about 10 seconds, until the shade button blinks and remains lit.

Step 3: Use the control's **Raise** and **Lower** buttons to adjust the shade position to the lower limit you prefer.

Step 4: Hold the **Close** button on the Pico for about 10 seconds, until the shade button blinks and turns off.



Roller shade

Upper Limit:

Step 1: Follow Steps 1- 3 of the Lower Limit steps.

Step 2: Hold the **Open** button on the Pico for about 10 seconds until the shade button blinks and turns off.

Quick reference guide Serena® Programming




Set a favorite level for shades

Note: Shade must be assigned to control.

Step 1: Use the control's **Raise** and **Lower** buttons to adjust the shade to desired level.

Step 2: Hold the **Favorite** button on the Pico® for about 10 seconds until the shade button blinks.



Restoring Shades to Factory Default

Note: This step will remove any controls assigned to the shade. It will not affect the shade's upper and lower limits.

Step 1: Tap the **shade button** quickly 3 times, and hold the **shade button** after the third tap until the shade button LED blinks green rapidly.

Step 2: Immediately tap the **shade button** quickly three more times, until the shade button LED blinks green rapidly, then blinks red/green three times, and turns off.

24/7 Technical Support 888.445.8063
www.lutron.com/serena

©09/2013 Lutron Electronics Co., Inc. | P/N 367-2428 REV B

